


**Cat # P2330 series Category 5 splitter**



These white coloured splitters enable two different devices to share the same cable and outlet. The narrow width and vertically mounted sockets are ideal for patch panels, allowing easy access to neighbouring patch-panel sockets. Five different wiring configurations are available. The wiring configuration-diagram is printed on the side of each splitter.


**P2332**



Splits a 4-pair 568B jack; pairs 1 & 2 to jack 1 and pairs 3 & 4 to jack 2.

Typical application would be voice at both jacks.


**P2334**



Splits a 4-pair 568A / 568B jack; pairs 2 & 3 to jack 1 and pairs 1 & 4 to jack 2.

Typical application would be data (10Base-T) at both jacks


**P2335**



Splits a 4-pair 568A jack; pairs 1 & 2 to jack 1 and pairs 3 & 4 to jack 2.

Typical application would be voice at both jacks


**P2336**



Splits a 4-pair 568A / 568B jack; pairs 2 & 3 to jack 1 and pairs 1 & 4 to jack 2.

Typical application would be data (10Base-T) at jack 1 and voice at jack 2.

**P2337**



Provides a second paralleled jack.